

NERTZ

hertzaudiovideo.com









1000W

KEY FEATURES



ULTRA POWER IN COMPACT SIZE

HMD1 mono amplifier is the perfect solution to add one or more marine subwoofer to your vassel, being the ideal power extension of HMD8 DSP. At 1 Ohms it is stable and can supply up to 1000 W of power with extremely compact dimension.



Hertz advanced D-CLASS output stage ensures pure listening pleasure while keeping a compact size with unmatched power efficiency.



| POWER SUPPLY | |
|--|----------------------------------|
| Power supply voltage / fuse | 11 ÷ 15 VDC / 2 x 30A |
| Operating power supply voltage | 6.5 ÷ 17 VDC |
| Idling current | 1.3 A |
| Idling current off | 0.05 mA |
| Consumption @ 14.4 VDC, 2Ω, Max Musical Power | 50 A |
| Remote IN | 6.5 ÷ 15 VDC (1 mA) |
| ART - Automatic Remote Turn on/off from OUTPUT BTL speakers (Selectable) | 2 ÷ 7 VDC |
| AMPLIFIER STAGE | |
| Distortion - THD @ 1 kHz, 4Ω, 70% Rated Power | 0.1% |
| Damping factor @ 1 kHz, 4Ω, 2 VRMS | 140 |
| Bandwidth @ -1.5 dB | 10 Hz ÷ 500 Hz |
| S/N ratio (A weighted @ 1 V Input) Master Input | 110 dBA |
| Input sensitivity Pre-In | Selectable: 0.6 - 2.0 - 6.0 VRMS |
| Input sensitivity Speaker-In | Selectable: 2.0 - 6.5 - 20 VRMS |
| Minimum load impedance | 1Ω |

| OUTPUT POWER (RMS) @14.4 VDC, 1% THD: | |
|---------------------------------------|------------------------------------|
| 1Ch @ 4Ω | 500 W |
| 1Ch @ 20 | 800 W |
| 1Ch @ 10 | 1000 W |
| INPUTS / OUTPUTS | |
| Pre-In Inputs | RCA |
| Speaker-In Inputs | Wired |
| SIZE | |
| Max size W x H x D (mm/inch) | 243 x 48 x 159 / 9.56 x 1.8 x 6.25 |
| Weight (kg/lbs) | 1,98 / 4.36 |

